



Topic 6: Radiation Fundamentals

Academic Year 2013 - 2014



- P1.-** Suppose a transmission power $P_{Tx} = 6\text{dBW}$. Obtain:
- The radiation intensity and the radiation density, at a distance of 100m, of an isotropic antenna.
 - The radiation intensity and the radiation density, at a distance of 200m, of a directive antenna with gain 3dB.

- P2.-** Obtain:
- The gain of an antenna with directivity 19dBi and efficiency 84,5%.
 - The directivity of an antenna with gain 15,54dB and efficiency 90%.

- P3.-** Prove that the basic losses in dB are:

$$L_{bf}(dB) = 92,45 + 20\log f(GHz) + 20\log d(km)$$

or

$$L_{bf}(dB) = 32,45 + 20\log f(MHz) + 20\log d(km)$$

- P4.-** Suppose a communication system in free space, with frequency 2,4GHz and isotropic antennas. The transmission power is 1W and the sensitivity (minimum received power) is -60dBm. Obtain:

- The maximum distance of the link.
- The maximum distance of the link taking into account a polarization loss of 1,5dB.
- If the link distance was 500m and it could change the transmitting antenna, what is the minimum G_{Tx} required?
- In a 500m link with the original antennas, what is the maximum frequency at which the link would be feasible?

CLASES PARTICULARES, TUTORÍAS TÉCNICAS ONLINE
LLAMA O ENVÍA WHATSAPP: 689 45 44 70

ONLINE PRIVATE LESSONS FOR SCIENCE STUDENTS
CALL OR WHATSAPP:689 45 44 70